

Production Server Reply Error Codes

The error numbers and corresponding descriptions listed below are returned in the ProductionServerReply XML message in the "CommandErrorCode" attribute of the "ProductionServerReply" element.

000	Successful result	305	Attempted to resume an order that is not suspended
100	Unrecognizable message or bad message format	306	Attempted to suspend an order that is already suspended
101	Invalid data for the command	307	Not used
102	Not used	308	Specified order is currently being canceled
103	Command is not supported in this Protocol	309	Not used
104	Not used	310	Order does not exist or is no longer active
105	Not used	311	Not used
106	Not used	312	Specified order quantity has already been produced
107	Not used	313	Not used
108	Shutdown is in progress	314	Unknown action specified for order
109	System too busy to handle request at this time	315	The specified order quantity is not valid
110	Parameter name is obsolete	330	Specified autoloader is disabled
111	Not used	331	Specified recorder is disabled
112	Not used	332	Specified printer is disabled
113	Not used	350	Not used
115	Not a valid dialog selection	351	Not used
116	Specified dialog was already answered or was not found	352	Data transmission timed out during device flash update
118	Server password is required for this request	353	Command sent while a flash data upload is occurring
119	Password is invalid	354	Not used
120	Not used	356	Flash firmware does not match any connected autoloader
121	Data for parameter value is out of range or invalid	357	Unable to open flash file
122	Server must first be paused	358	Unable to determine size of flash file
126	Server has not yet finished initializing	359	Unable to get the version number of the flash file
127	Not used	360	Error occurred while uploading flash file data to device
128	Not used	361	Printer flash file must be exactly 65536 bytes in length
129	Unable to change to Kiosk mode while in Job Streaming	362	Update flash operation failed in device initialization
130	Kiosk mode not settable in Bulk Read mode	363	No recorders can be updated with flash file
131	Both CD-R and DVD-R input bins are required	364	Unable to allocate needed buffer space for update flash operation
132	At least 1 input only or input/output bin is required	365	Unable to access a required offset in the flash
133	At least 1 output only or output/reject bin/slot is required	366	No printers can be updated with the flash file
134	Mailslot is disabled due to small media size, no output specified	367	Unable to change baud rate of device in update flash operation
167	No CD-R drives in loader	368	Flash file is not intended for this device
169	No recorders in loader	371	Flash update operation was ended due to unknown reason
170	No reader attached to Server	380	Not Used
171	Verify frequency must be in range 1 to 1000 discs	381	Device is already enabled
172	Invalid barcode angle was specified	382	Specified autoloader does not exist
200	Internal error Server's Status and Control software	383	Specified recorder does not exist
201	Not used	384	Specified printer does not exist
202	Not used	385	Attempt made to enable a manual loader
304	Suspended orders may not be resumed on a paused system		